

## **SOFTWARE BULLETIN C.P.U. VERSION V3.02 FOR NAGRA-D**

The software V3.02 for the C.P.U. of the NAGRA-D has been introduced principally for the NAGRA-DII machines. The time code version remains V3.02 as before.

A 60g tape tension menu has been added to the OTHERSET menu to allow the tape tension to be increased in order to improve the tape handling of QUANTEGY 467 tape on the NAGRA D-II. This is necessary because the reduced tape tension on the NAGRA-DII due to the new rotating scanner guides means that the more flexible Quantegy 467 tape does not pass across the scanner correctly. This position should be selected when QUANTEGY 467 is being used on the NAGRA-DII. This is not necessary on the NAGRA -D (serial number lower than 1001101).

A non time code NAGRA-D or D-II will no longer put a time code value in the directory even if the time code record inhibit switch is in the READY position.

In the REF FREQ. Menu the 9600Hz reference position is operational again. (Since Version V3.00 this position would put the machine in REF 96 kHz by mistake).

The AES Output mode (1 Wire / 2 Wires) is no longer set to the same mode as the AES Input mode when the machine is powered up.

NAGRAVISION S.A  
15 March 2000